

CGSNGTFT Datasheet

Natural Gas Detector











Alarm Relay Dry Contact



Plug & Play Installation



Product Overview


The TFT range of CGS detectors work in combination with the CGS Merlin range of Gas Detection panels and Utility Controllers. The CGSNGTFT features a semiconductor sensor for industrial and commercial indoor applications. Compact, modern, digital design makes the units aesthetically pleasing and easy to install.

Popular Applications



Technical Specification

General							
Model:		Merlin Gas Detector TFT					
Target Gases:		NG					
Size: (H x W x D)		5.51 x 3.74 x 1.18" (140 x 95 x 30mm)					
Housing Material:		ABS Polylac - PA765					
Mounting:		Safe Zone - Indoor use - Wall Mounted					
Weight:		Max. 1.77oz (0.05kg)					
User Interface							
Display:		1.8" TFT					
Screen Brightness:		Non-Adjustable					
Visual Indicators:		TFT visual. Green: Normal; Yellow: Pre-Alarm; Red: Alarm					
Audible Alarm:		>70dB @ 3.28ft (1m). Quiet conditions.					
Buttons:		None					
Language:	English						
Power Supply							
Power Consumption:		90mA Max @ 24vdc					
DC Power:		12-32 VDC - Nominal 24 VDC					
Internal Fuse:		None					
Equipment							
Overvoltage Category:		III					
Pollution Degree:		3					
I/O							
Relay:		Volt Free (Normally Closed / Common / Normally Open)					
Relay.		1x 30vdc 2A (Non-Latching)					
Environmental							
Ingress Protection:		Not Formally Evaluated					
Operating:		-10 ~ 50°C / 14 ~ 122°F 30 ~ 80% RH (non-condensing)					
Storage:		-25 ~ 50°C / -13~122F° up to 95% RH (non-condensing)					
Altitude Rating:		2000m					
Wiring							
Typical		#15AWG Power Pair; #18AWG Data Pair-Tinned copper.					
Approvals							
Electromagnetic Compatibility and		BS/IEC/EN 61010-1					
Electrical Safety		EMC EN 50270					
Other							
Communication		RS485 MODBUS RTU					
Gas Sensor	Indicating Range	Steps	Response (t90)	Recovery (t10)	Alarm: 1 (Pre alarm warning)	Alarm: 2	* EOL (Years)
Methane (CH4)	0-20%LEL	0.1	<30s	<30s	▼8% LEL	▼10% LEL	10



Area of coverage

Consider the coverage required and function of the area. Emphasis should be placed on airflow patterns and correct placement, not perceived detecting ranges. The target gas will only be identified when contact is made with the sensing element itself.

The CGSNGTFT monitor should be installed approximately 1ft from ceiling.

Find out more Canadian Gas Safety Inc

www.canadiangassafety.com

Head office: 150 King Street West Suite 200, Toronto, ON M5H 1J9 Tel: (647) 577-1500 Email: info@canadiangassafety.com

